

General data of Antenna System

TX station	1+1Akl5
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	98.000
Antenna system central frequency (MHz)	98.000
Antenna base diagrams type 1	LABEL ITALY-AKL_5 LOG 5 ELEM. FM WB
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	AKL_5 LOG 5 ELEM.
Band start(MHz)	88
Band stop(MHz)	108
diagrams Frequency(MHz)	98
Polariz (H,V,C,X)	V
Vertical dist (cm)	260
Height (cm)	173
Width (cm)	6
Thickness (cm)	143
Weight (Kg)	4.5
Maximum power (KW)	2
Gain (dBd)	6.2
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	20
R.C.Phase (°)	0

TX station: 1+1AkI5

Frequency: 98.00 MHz


Gain solid integration : enabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)		<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	50.000	0	0	0 +0.0		0.00	80.0	270.0	1	1	0.0	0.0
2	50.000	0	0	0 +0.0		0.00	80.0	90.0	1	1	0.0	0.0

Plan of antenna system



Side of antenna system



TX station: 1+1Akl5
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly


Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	2
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	8.74
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	8.74
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	8.74
K. Effec. max gain (times)	7.48
L. Effec. max power [E * K] (KW)	7.4767
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	0

Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	8.7	90	-11.3	180	-11.3	270	-11.3
10	8.2	100	-11.3	190	-11.3	280	-11.3
20	6.9	110	-11.3	200	-11.3	290	-11.3
30	4.6	120	-11.3	210	-11.3	300	-11.3
40	1.1	130	-11.3	220	-11.3	310	-4.0
50	-4.0	140	-11.3	230	-11.3	320	1.1
60	-11.3	150	-11.3	240	-11.3	330	4.6
70	-11.3	160	-11.3	250	-11.3	340	6.9
80	-11.3	170	-11.3	260	-11.3	350	8.2

Horizontal diagram at 0.0° depres. (Total Antenna)




0.0° depres. (Total Antenna), Gain (dBd): 8.74

ERP T.Max(KW): 7.4767

ERP E.Max(KW): 7.4767

Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 8.74

ERP T.Max(KW): 7.4767 ERP E.Max(KW): 7.4767