

TX station: 6xBkv1-2  
Gain solid integration : disabled

Site Name: Labelitaly

### General data of Antenna System

TX station	6xBkv1-2
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	220.000
Antenna system central frequency (MHz)	220.000
Antenna base diagrams type 1	LABEL ITALY-BKV_1-2 VHF DIPOLE
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

### Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	BKV_1-2 VHF DIPOLE
Band start(MHz)	200
Band stop(MHz)	240
diagrams Frequency(MHz)	220
Polariz (H,V,C,X)	V
Vertical dist (cm)	150
Height (cm)	65
Width (cm)	6
Thickness (cm)	63
Weight (Kg)	3.5
Maximum power (KW)	1.5
Gain (dBd)	2.1
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	20
R.C.Phase (°)	0

TX station: 6xBkv1-2  
Frequency: 220.00 MHz  
Gain solid integration : disabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)	<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	16.667	0	0	0 +0.0	3.25	0.0	0.0	1	1	0.0	0.0
2	16.667	0	0	0 +0.0	1.95	0.0	0.0	1	1	0.0	0.0
3	16.667	0	0	0 +0.0	0.65	0.0	0.0	1	1	0.0	0.0
4	16.667	0	0	0 +0.0	-0.65	0.0	0.0	1	1	0.0	0.0
5	16.667	0	0	0 +0.0	-1.95	0.0	0.0	1	1	0.0	0.0
6	16.667	0	0	0 +0.0	-3.25	0.0	0.0	1	1	0.0	0.0

TX station: 6xBkv1-2  
Frequency: 220.00 MHz  
Gain solid integration : disabled

Site Name: Labelitaly

Plan of antenna system



Side of antenna system



TX station: 6xBkv1-2  
Frequency: 220.00 MHz  
Gain solid integration : disabled

Site Name: Labelitaly

Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	6
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	9.88
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	9.88
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	9.88
K. Effec. max gain (times)	9.73
L. Effec. max power [E * K] (KW)	9.7309
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	340


Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	9.9	90	7.0	180	3.7	270	7.0
10	9.9	100	6.1	190	3.7	280	7.8
20	9.9	110	5.2	200	3.8	290	8.6
30	9.8	120	4.6	210	3.9	300	9.1
40	9.7	130	4.2	220	4.0	310	9.5
50	9.5	140	4.0	230	4.2	320	9.7
60	9.1	150	3.9	240	4.6	330	9.8
70	8.6	160	3.8	250	5.2	340	9.9
80	7.8	170	3.7	260	6.1	350	9.9

TX station: 6xBkv1-2  
Frequency: 220.00 MHz  
Gain solid integration : disabled

Site Name: Labelitaly

### Horizontal diagram at 0.0° depres. (Total Antenna)




0.0° depres. (Total Antenna), Gain (dBd): 9.88

ERP T.Max(KW): 9.7309 ERP E.Max(KW): 9.7309

TX station: 6xBkv1-2  
Frequency: 220.00 MHz  
Gain solid integration : disabled

Site Name: Labelitaly

## Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 9.88

ERP T.Max(KW): 9.7309 ERP E.Max(KW): 9.7309